

---

## 40 C.F.R. § 761.2

---

### PCB concentration assumptions for use.

---

(a)

(1) Any person may assume that transformers with <3 pounds (1.36 kilograms (kgs)) of fluid, circuit breakers, reclosers, oil-filled cable, and rectifiers whose PCB concentration is not established contain PCBs at <50 ppm.

(2) Any person must assume that mineral oil-filled electrical equipment that was manufactured before July 2, 1979, and whose PCB concentration is not established is PCB-Contaminated Electrical Equipment (i.e., contains  $\geq 50$  ppm PCB, but <500 ppm PCB). All pole-top and pad-mounted distribution transformers manufactured before July 2, 1979, must be assumed to be mineral-oil filled. Any person may assume that electrical equipment manufactured after July 2, 1979, is non-PCB (i.e., <50 ppm PCBs). If the date of manufacture of mineral oil-filled electrical equipment is unknown, any person must assume it to be PCB-Contaminated.

This document is only available to subscribers. Please [log in](#) or [purchase access](#).

[Purchase Login](#)